

RESETTING GENERAC POWER PACT 7.5KW



This is the process for resetting a generator when it has a fault code (red light). Before starting to reset the generator, look at the screen that is above the buttons. It will display a fault code and the meaning. Please write down what it says before starting the process. This helps us before coming out to repair if needed.

Resetting your Generator:

- 1.) If your generator is in fault, one of the little lights by the error codes will be lit up. Record this fault, then press the **RED** OFF button.
- 2.) Wait 15 seconds after pressing OFF, then press the **BLUE** MANUAL button. The machine will try to start and run.
- 3.) If the machine runs, let it run for 15 minutes then use the OFF button to turn the machine off. If the machine fails to start or goes into fault, then leave it off and call 815-675-1555 for service.
- 4.) If the machine starts and runs for the 15 minutes and has no issues, after turning it OFF, press the **GREEN** AUTO button to return to standby mode. If the AUTO button is not pressed, the machine will not run in the event of an outage.